

## PRO9 HEADSET SYSTEM

for team communication

### Pro9 for Quick Service

The all-new Pro9 headset system for Quick Service is a huge step-change in simplicity, comfort and audio clarity.

Pro9 is a multi-channel headset designed for single and dual lane drive-thru, curb-side ordering and in-restaurant table service, all from the same headset.

And, its range will cover kitchen, seating on two floors, drive-thru lanes, drive-to bays and parking lot.

There's no limit to the number of headsets you can use on the system, with contactless registration and Puresound noise cancelling much improving the user experience.





### Headset

**Operating frequency**  
**Channels**  
**Channel activation**  
**Paging**  
**LEDs**  
**Volume adjustment**  
**Noise cancelling**  
**Sleep mode**  
**Registration**  
**Battery**  
**Audio prompts**  
**Weight**  
**Approvals**

### Q-P9HS

1.88-1.90GHz EMEA, Asia; 1.91-1.93GHz North America  
 T1, T2, TS1 (table service), P (paging)  
 Order taker press T1 or T2; runner press T1 + P or T2 + P; table service press P twice  
 Press and hold page button  
 T1 green, T2 blue, TS amber, P white  
 5 stepped levels  
 Acoustic noise cancelling to orderpoint speaker  
 Activated after 10 mins of headset being motionless  
 Near-field wireless IR link  
 750mAh, 3.7v lithium-ion polymer  
 Audio beep indicates change of status  
 120g with battery  
 EN301 406 v2.2.2 FCC Part 15 IC RSS-213. EMC ETSI EN 301 489-1 V2.2.0 Accoustic energy EN 62368-1 SARS IEEE Std 1528 & FCC requirements




### Base Station

**Headset capacity per lane**  
**Range**  
**Dual lane capability**  
**Power**  
**Connectivity**  
**Features**  
**System settings**  
**Status of LEDs**  
**Headset registration**  
**Dimensions / weight**  
**Approvals**

### Q-P9BS

Order-taker/unlimited runners hearing order-taker/customer, all communicate on paging channel  
 50m radius from base depending on environment, extendable with up to 2 repeaters (Q-P9REP)  
 Dual lane plus table service; dual lane systems use 2 x Q-P9BSDL variant base  
 100-240v AC voltage sensing  
 Power via DC jack; CAT5/6 to Q-P9BSDT + Q-P9BSTS bases + Q-P9DTM; 7Pin DIN to grill speaker/timer  
 Ethernet API; push buttons for loop override, system reset, tandem order taking, night volume & grill speaker volume adjustment; at-a-glance fault diagnosis using front enclosure LED display  
 Factory settings as standard on arrival; all setting adjustments can be made on site via API  
 Power ON, car arrival, order-taker talking to customer, colour-coded fault diagnosis  
 Near-field wireless IR link  
 250x160x43mm (HxWxD) / 405g  
 EN301 406, FCC Part 15 (D), IC RSS-213, EMC ETSi EN 301 489-1



### Repeater

**Range**  
**Power**  
**Connectivity**  
**LEDs**  
**Dimensions / weight**

### Q-P9REP

50m radius depending on environment; 2 repeaters max per base  
 100-240v AC voltage sensing  
 Cat5/6/7 cable from base  
 Power ON, car arrival, order taker talking to customer, colour-coded fault diagnosis  
 250x160x43mm (HxWxD) / 310g



### Charger

**Capacity**  
**Battery charge time**  
**LED indicators**  
**Power**  
**Dimensions / weight**

### Q-P9CH

8 batteries  
 4 hours full charge; recommend change battery from 500 charge cycles  
 Red power light; individual lights for each battery, red charging, green fully charged  
 100-240v AC voltage sensing  
 205x325x45mm (HxWxD) without bar / 710g



### Drive-thru module

**Function**  
**Detection**  
**Connector type**  
**Power**  
**Screening and waterproof**  
**Dimensions / weight**

### Q-P9DTM

Process and digitalise clean audio from speaker and microphone to order taker and back  
 Vehicle detector loop included; connections only for sonar  
 IP rated RJ45 network; locked connectors for speaker and microphone  
 Via network cable 48v  
 Sealed metal enclosure and using IP rated connectors  
 252x170x55mm (HxWxD) without connector covers / 880g



### Loudspeaker & enclosure

**Type**  
**Watts / power peak**  
**Impedance**  
**Frequency response**  
**Connectivity**  
**Dimensions / weight**

### Q-P9SPK

Mylar waterproof speaker, enclosure rated IP64  
 15 watts / 30 watts  
 8 ohms  
 210 to 7000Hz  
 4 pin locking GX16 connector  
 117x117x73mm (HxWxD) without bracket / 682g



### Microphone & enclosure

**Type**  
**Sensitivity**  
**Impedance**  
**Connectivity**  
**Dimensions / weight**

### Q-P9MIC

Dynamic omni-directional; enclosure rated IP64  
 200 to 10000Hz  
 50 ohms  
 3 pin locking GX16 connector  
 117 x 117 x73mm (HxWxD) without bracket / 438g